

PPR No.							
Switch settings							
sw1	sw2	sw3	sw4	sw5	sw6	sw7	
0	0	0	0	0	0	0	0.5
1	0	0	0	0	0	0	1
0	1	0	0	0	0	0	1.5
1	1	0	0	0	0	0	2
0	0	1	0	0	0	0	3
1	0	1	0	0	0	0	4
0	1	1	0	0	0	0	5
1	1	1	0	0	0	0	6
0	0	0	1	0	0	0	8
1	0	0	1	0	0	0	8.1
0	1	0	1	0	0	0	8.2
1	1	0	1	0	0	0	8.3
0	0	1	1	0	0	0	8.4
1	0	1	1	0	0	0	8.5
0	1	1	1	0	0	0	8.6
1	1	1	1	0	0	0	8.7
0	0	0	0	1	0	0	8.8
1	0	0	0	1	0	0	8.9
0	1	0	0	1	0	0	9
1	1	0	0	1	0	0	9.1
0	0	1	0	1	0	0	9.2
1	0	1	0	1	0	0	9.3
0	1	1	0	1	0	0	9.4
1	1	1	0	1	0	0	9.5
0	0	0	1	1	0	0	9.6
1	0	0	1	1	0	0	9.7
0	1	0	1	1	0	0	9.8
1	1	0	1	1	0	0	9.9
0	0	1	1	1	0	0	10
1	0	1	1	1	0	0	10.1
0	1	1	1	1	0	0	10.2
1	1	1	1	1	0	0	10.3
0	0	0	0	0	1	0	10.4
1	0	0	0	0	1	0	10.5
0	1	0	0	0	1	0	10.6
1	1	0	0	0	1	0	10.7
0	0	1	0	0	1	0	10.8
1	0	1	0	0	1	0	10.9
0	1	1	0	0	1	0	11
1	1	1	0	0	1	0	11.1
0	0	0	1	0	1	0	11.2
1	0	0	1	0	1	0	11.3
0	1	0	1	0	1	0	11.4
1	1	0	1	0	1	0	11.5
0	0	1	1	0	1	0	11.6
1	0	1	1	0	1	0	11.7
0	1	1	1	0	1	0	11.8
1	1	1	1	0	1	0	11.9

PPR No.							
Switch settings							
sw1	sw2	sw3	sw4	sw5	sw6	sw7	
0	0	0	0	1	1	0	12
1	0	0	0	1	1	0	12.1
0	1	0	0	1	1	0	12.2
1	1	0	0	1	1	0	12.3
0	0	1	0	1	1	0	12.4
1	0	1	0	1	1	0	12.5
0	1	1	0	1	1	0	12.6
1	1	1	0	1	1	0	12.7
0	0	0	1	1	1	0	12.8
1	0	0	1	1	1	0	12.9
0	1	0	1	1	1	0	13
1	1	0	1	1	1	0	13.1
0	0	1	1	1	1	0	13.2
1	0	1	1	1	1	0	13.3
0	1	1	1	1	1	0	13.4
1	1	1	1	1	1	0	13.5
0	0	0	0	0	0	1	13.6
1	0	0	0	0	0	1	13.7
0	1	0	0	0	0	1	13.8
1	1	0	0	0	0	1	13.9
0	0	1	0	0	0	1	14
1	0	1	0	0	0	1	14.25
0	1	1	0	0	0	1	14.5
1	1	1	0	0	0	1	14.75
0	0	0	1	0	0	1	15
1	0	0	1	0	0	1	15.25
0	1	0	1	0	0	1	15.5
1	1	0	1	0	0	1	15.75
0	0	1	1	0	0	1	16
1	0	1	1	0	0	1	16.25
0	1	1	1	0	0	1	16.5
1	1	1	1	0	0	1	16.75
0	0	0	0	1	0	1	17
1	0	0	0	1	0	1	17.25
0	1	0	0	1	0	1	17.5
1	1	0	0	1	0	1	17.75
0	0	1	0	1	0	1	18
1	0	1	0	1	0	1	18.25
0	1	1	0	1	0	1	18.5
1	1	1	0	1	0	1	18.75
0	0	0	1	1	0	1	19
1	0	0	1	1	0	1	19.25
0	1	0	1	1	0	1	19.5
1	1	0	1	1	0	1	19.75
0	0	1	1	1	0	1	20
1	0	1	1	1	0	1	20.25
0	1	1	1	1	0	1	20.5
1	1	1	1	1	0	1	20.75

PPR No.							
Switch settings							
sw1	sw2	sw3	sw4	sw5	sw6	sw7	
0	0	0	0	0	1	1	21
1	0	0	0	0	1	1	21.25
0	1	0	0	0	1	1	21.5
1	1	0	0	0	1	1	21.75
0	0	1	0	0	1	1	22
1	0	1	0	0	1	1	22.25
0	1	1	0	0	1	1	22.5
1	1	1	0	0	1	1	22.75
0	0	0	1	0	1	1	23
1	0	0	1	0	1	1	23.25
0	1	0	1	0	1	1	23.5
1	1	0	1	0	1	1	23.75
0	0	1	1	0	1	1	24
1	0	1	1	0	1	1	24.25
0	1	1	1	0	1	1	24.5
1	1	1	1	0	1	1	24.75
0	0	0	0	1	1	1	25
1	0	0	0	1	1	1	25.25
0	1	0	0	1	1	1	25.5
1	1	0	0	1	1	1	25.75
0	0	1	0	1	1	1	26
1	0	1	0	1	1	1	26.25
0	1	1	0	1	1	1	26.5
1	1	1	0	1	1	1	26.75
0	0	0	1	1	1	1	27
1	0	0	1	1	1	1	27.25
0	1	0	1	1	1	1	27.5
1	1	0	1	1	1	1	27.75
0	0	1	1	1	1	1	28
1	0	1	1	1	1	1	28.25
0	1	1	1	1	1	1	28.5
1	1	1	1	1	1	1	28.75

Switch setting '1' signifies on
Switch setting '0' signifies off

Setting example:

Four cylinder, single spark engine

PPR is 2

From table, switch setting is:

Sw1	sw2	sw3	sw4	sw5	sw6	sw7
1	1	0	0	0	0	0
on	on	off	off	off	off	off

Note: Switch number 8 should always be in the 'on' position.